




Sky Eye-30HZ

1080P 30X Zoom Camera



Warning and Disclaimer

Make sure not to adjust the gimbal or change its mechanical structure by yourself. Be sure to mount the camera to gimbal before power on, and then install the gimbal on the aircraft.


To avoid gimbal performance degradation or damage caused by imbalanced payload, please do not add other peripherals for the gimbal camera (filter, hood, etc).

When in aerial photography, make sure your aircraft flight control system is working at the safe mode.

We strongly recommend that you remove aircraft propellers before doing gimbal configuration. Use extra non-power battery for gimbal. Keep children away from the preset flight region.

Considering that we are not able to control user's specific usage, installation, assembly, modification (including the use of non-specified parts), and improper use. Direct or indirect damage or injury caused by the behavior above, our company will not cover any loss and responsibility.

Gimbal description



[1]Control box

[3]Damping ball

[5] Lower damping board

[7]Roll axis motor

[9]HD zoom camera

[2] Gimbal fixed copper cylinder

[4]Upper damping board


[6]YAW axis motor

[8]Pitch axis motor




Please make sure that the motor is not stopped by any object during the rotation, if the gimbal is blocked during rotation, please remove the obstruction immediately.


Packing List




Gimbal camera*1



Damping board*2




Copper cylinders*4



Anti shedding buckle*4





5mm*12



8mm*4


Button head hexagon screw*16

Gimbal Camera Dimension




Unit :mm

Connection of Control Box and Wiring Instruction




← Control Box position



1. Insert SD card

SD card: max 32G , class10

FAT32 or exFAT format




SD card position

2. Connect HDMI to display




HDMI : micro HDMI OUTPUT

1080P 60fps default




HDMI position

3. Connect the signal line as below



4. Power supply with 12V, red line is positive and black is negative.



Function Description

Gimbal control

- Yaw axis control:speed mode,connect Rocker channel(or 3 gears channel,push gear to middle position to stop)
- Pitch axis control:speed mode,connect Rocker channel(or 3 gears channel,push gear to middle position to stop)
- Mode control:angle mode,connect knob channel(speed mode:connect 3 gears channel or rocker channel)

If connecting knob channel,rotate to one end,the gimbal is at lowest speed when controlling YAW and PITCH axis.

Rotate the knob to any position,gimbal is at higher speed when controlling YAW and PITCH axis.Rotate to knob to another end,gimbal back to center position.

Camera control


1. Zoom control:connect 3 gears or rocker channel
2. Focus:connect 3 gears or rocker channel for manual focus control.
If do not connect any channel,then camera will auto focus after zooming
3. PIC:connect 3 gears channel

Flip the gear from middle position to high position,record/capture mode switch

Flip the gear from middle position to low position:

- A:If under record mode:record start,flip from middle to low again,record stop
 - B:If under capture mode,capture start
4. REC(start/stop record backup PIN):connect 3 gears channel if this PIN is needed
 - **A:** Under record mode
Flip the gear from middle to high : record start
Flip the gear from middle to low : record stop
 - **B:** Under capture mode
Flip the gear from middle to high : capture start

Signal functions





S.bus/Rx: connect to Rx2 for track function.

Roll/ Tx: connect to Tx2 for track function.

Pitch: PWM in, pitch control

Pitch: PWM in, pitch control



Yaw: PWM in, Yaw control



1 Yaw right




2 Yaw stop



3 Yaw left

Mode: Change the speed / home position






- Position 1: Lowest speed for pitch and yaw.
- Position 2: Middle speed for pitch and yaw.
- Position 3: Highest speed for pitch and yaw.


The speed is continuously quickly from 1 to 3.

- One click: Home position.
- Two click: Look down.
- Three click: Yaw not followed by frame.
- Four click: Yaw followed by frame.
- Five click: Restore the factory settings.

(Click = from 2 to 3 and back to 2 quickly)

Zoom: Zoom the camera**Focus: Focus the camera****Pic/ Rec picture / Start record, stop record**

1. Switch 2 to 1: Start record / stop record.
Start record, the OSD display rec hh:mm:ss ;
2. Stop record, the OSD display STBY.
3. Switch 2 to 3: Take a picture. OSD display 'REC IMG' a second.

Multi: backup PWM channel for customize**AV: AV output .**

30X zoom camera

Sensor	1/3 inch 3MP CMOS SENSOR
Video Output	CVBS and 1080P/60 HDMI
Video recorded	1080P/30 MP4
Focal length	30X optical focal zoom, 4.5-135mm
Wide Dynamic	Up to 105dB
FOV	Horizontal: 54.8°(Wide end) ~ 3.4°(Tele end)
	Vertical: 41°(wide end) ~ 2.5°(tele end)
	Focus: 66.6°(wide end) ~ 7.2°(tele end)
Auto focus	Less than 1S
Low illumination	0.05lux@F1.6
Aperture	Φ 16.0
Vertical Roll / Horizon Mirror/Static	Support
AWB/AGC/ACC/	Support
Input voltage	3S-4S
Rotate range	Pitch: ±90° Roll: ±45° Yaw: ±150°
Angle amount of jitter	Pitch and roll: ±0.02° Yaw: ±0.03°
Control interface	PWM, S.Bus and serial command
Working Current	Static current: 330mA(@12V)
	Dynamic current: 450mA(@12V)
Total weight (gimbal and camera)	848g
Working temperature	-25° ~ +60°